

Y SERIES

Wall Mounted

Lithium Battery

51.2 V 200AH 10.24 KWH

- Safety and Intelligent
 Long life LiFePO4 cells, high energy density,
 build in BMS and passive protection
- Easy to Install and Use Modular design, simple operation
- Long Life Span
 10 years design life, more than 6000cycles

- Adaptable to Harsh Environment
 Adapt to wide range of temperature and humidity
- · Support Bluetooth/WIFI function (optional)

Can be controlled remotely to reduce operation and maintenance costs

• Multi-scenario application Household use, small industrial and commercial applications





Technical Parameters

| Nominal voltage | 51.2V |
|------------------------------|--|
| Nominal capacity | 200Ah |
| Energy | 10.24kwh |
| Interal Resistance | ≤200mΩ |
| Cycle Life | >6000 cycles @ 0.2C 80%D.O.D |
| Months Self Discharge | <3% |
| Efficiency of Charge | 99.5%@ 0.20 |
| Effciency of Discharge | 96-99%@ 10 |
| Charge Voltage | 58.4±0.5V |
| Charge Mode | CC/CV |
| Charger Current | 404 |
| Max Charge Current | 200A |
| Charge Cut-off Voltage | 58.4 |
| Continuous discharge Current | 40A |
| max discharge Current | 200A |
| Discharge Cut-off Voltage | 43.2V |
| Charge Temperature | 0°C to 45 °C |
| Discharge Temperature | -20 ℃ to 55 ℃ |
| Storage Temperature | -10 °C to 40 °C |
| Water Dust Resistance | IP20(IP54 OPTIONAL |
| Size (mm) | 780*505*168(D*W*H) |
| Weight (kg) | 90kg |
| Terminal | 200A |
| Protocol (optional) | RS232/RS485/CAN/BLUETOOTH/WIF |
| BMS | 200A |
| Safety & Certification | CELL:UL1642/UL1973/IEC62619/CE/CB/UN38.3/UL9540/ROHS/REACH |
| Wooden box package size (mm) | 940*555*405 |
| Quantity of loading | 120pcs/20ft 240pcs/40ft |

Notes

- *1 Test conditions: Based on the factory date, charge and discharge rate at 0.2C at 100% discharge depth (DoD) and 25
- * 2 The weight of the battery module is based on the actual product, with a tolerance of $^{\pm}$ 3% allowed
- *3 The installation of battery packs is related to product quality assurance, safe and stable operation. Please follow the requirements of the user manual for standardized installation, use, and routine maintenance

Compatibility Inverters











SCIFAR





^{*}Only a part of inverter brands are shown, please contact us for more information.

